

7 Button Single Gang Keypad



gKP7



The ELAN gKP7 is international voltage compatible.

The Next Step in Home Control.

It's not too big, and definitely unassuming, but the ELAN gKP7 puts simple to use power where you need it. The gKP7 provides the end user with valuable back-lit control that always works, never runs out of batteries, and does what it says at a price that fits any budget.

The gKP7 was designed to aesthetically match the ELAN Lighting 7 button keypads and offers five completely programmable buttons and two raise/lower buttons with flexible functionality as well. Depending on your needs, the five function buttons may be mix and match programmed using ELAN Configurator to be used as a media favorite preset, to execute a lighting scene, act as zone/system off, or to execute an Event Mapper automated event. The bottom two raise/lower buttons may be configured to either operate zone volume or lower and raise a lighting scene or shade group. Using the ELAN Configurator interface personalization is simple and efficient.

As a media interface the gKP7 dedicates to one zone and allows the end user to conveniently store and recall; stations from any ELAN supported two-way tuner, playlists from an ELAN g1 MP3 player, channels and playlists from premium streaming content devices (Autonomic, LMS and Sonos), as well as access and initiate playback from legacy sources like CD players. All the end user must do is use a touch panel interface to access the desired media and then press and hold the Favorite button to store. Recalling is as simple as pressing the Favorite button.

For lighting you may assign a KP7 button to toggle any system lighting scene or dimmer. Pressing the button executes the lighting scene and lights the button's back-lighting. A second press turns the scene off as well as the button LED.

The Event Mapper puts the power of automation at your fingertip as gKP7 buttons may be programmed to do virtually anything through programming by an ELAN certified technician.

Want to turn off the lights, shut the blinds, and set back the thermostat? No problem. The Event Mapper even allows you to control the LED state for accurate feedback.

The lower two buttons may be programmed to either lower and raise the volume in the audio zone, the lighting of the last selected scene, or to perform custom Event Map actions.

The gKP7 ships with white buttons and bezel and includes 10 extra buttons for your convenience. Light almond (gKP7BK-LA) and black (gKP7BK-B) color change kits are available and include the bezel and all sixteen buttons included with the white gKP7.

gKP7 7 Button Single Gang Keypad



ORDER NO. GKP7

FEATURES

- 7-button backlit keypad
- Programmable through ELAN Configurator for five different button actions
- Custom engraveable buttons
- Gangable with any 1g device
- Comes in white with optional black or light almond bezel kit

Note: Decorator trim plate not included.

INCLUDED IN THE BOX:

- (1) gKP7 single gang keypad with white **Favorite 1-4, Off** and **V / A** buttons installed
- (2) Mounting screws
- (1) Quick Install Guide
- (1) Alternate button pack

SPECIFICATIONS	
Dimensions	4.12" x 1.75" x 1.24"
Mounting Depth	1.75"
Button type	<ul style="list-style-type: none"> • Contact type buttons • 5 individually capped • 2 shared for rocker capping • 5 individually controlled white LEDs for backlighting • 2 shared control white LEDs for backlighting
Connections	LAN/ PoE RJ-45 10/100/1000 Ethernet
Power Requirements	PoE (Power over Ethernet) IEEE 802.3at, 13w maximum draw (@48 V \approx 270 mA max.)



Comes in white with optional black or light almond bezel kit.

BUTTONS INCLUDED WITH KEYPAD

Favorite 1	Home Mode	😊
Favorite 2	Stay Mode	☁
Favorite 3	Away Mode	🌅
Favorite 4	Shade ⤴	⤴ ⤵
Off	Shade ⤵	
⤴ Vol ⤵	Mute	

Includes 16 pre-engraved buttons.

Custom engraving available.



gKP7BK-B Black Button Kit

ELAN[®]
Your world, made simple.™

www.elanhomesystems.com