

### **OPT-TX WB2**

Wide fibre



Wide Fibre transmitter to manage RF signals from two satellite dish equipped with wideband LNBs (V, H) and a digital terrestrial antenna, also combining FM and DAB radio signals.

The OPT-TX WB1 is equipped with **5 separate lasers** that can handle 4 **wideband polarities** and TV signal separately and uses **Coarse Wavelength Division Multiplexing** (CWDM) technology to combine the different optical wavelengths and transmit them on **a single-mode optical fiber** 9/125µm.

### **Technical Chars**

- 2 satellites with wideband LNB and input for TV, DAB and FM signals
- Compact size
- Dual DC input F type connectors for redundant power supply to ensure continuity of service
- AGC on all coaxial inputs for maximum signal processing stability
- Dedicated laser at each wideband SAT polarity and TV section, for maximum RF signal quality
- Status LEDs for each input for quick diagnostics
- Included power supply unit; the transmitter can also be fed from V and H inputs

| OPT-TX WB2          |      |   |
|---------------------|------|---|
| Code                |      | 270904  |
| Input RF            |      | 5 (4 SAT + 1 TV)  |
| Optical Output      |      | 1 x SC/APC  |
| Input TV            |      |   |
| Connectors          |      | F Female  |
| Input level         | dBµV | 63-90 @MUX  |
| Frequency band      | MHz  | 88-790  |
| Return loss         | dB   | 6   |
| SAT inputs          |      |   |
| Bandwidth           | MHz  | 290-2340  |
| SAT Connectors      |      | F Female  |
| Output level SAT    | dBµV | 60-85@TP  |
| Return loss         | dB   | 6   |
| Optical output      |      |   |
| Wavelength          | nm   | 1310 (SatA V), 1330 (SatA H), 1350 (SatB V), 1370 (SatB H), 1550 (TV) |
| Optical power       | dBm  | 6 (±1)  |
| Optical return loss | dB   | >30   |
| Safety class        |      | 1M  |

## Data sheet

# FRACARRO

#### Specifications

| Power supply voltage     | V  | 12-18  |
|--------------------------|----|--|
| Current consumption      | mA | 750@12V  |
| LED                      |    | <ul> <li>Green LED fixed ON: input RF signal in the correct operating range</li> <li>Green LED slowly blinking: input RF signal too low</li> <li>Green fast blinking: input RF signal too high</li> <li>Red LED fixed ON: possible failure of the corresponding laser</li> </ul> |
| Operating temperature    | °C | -10 to +55   |
| Storage temperature      | °C | -40 to +70   |
| Conformity               |    | CEI EN 50083-2 EN60065   |
| Dimensions and packaging |    |  |
| Pieces                   |    | 1  |
| EAN code                 |    | 8016978108527  |
| Product dimensions       | mm | 114 x 230 x 31   |