

GX-4C2CI-BP-00

Galaxia headend



GX-4C2CI-BP-00 receiver module is equipped with one RF coaxial input connector (F Female) and two PCMCIA Common Interface slots. The module is able to tune up to **four DVB-C digital QAM multiplexes**, decrypt the scrambled programs through the C.I. slots and share and pool the contents to the **GALAXIA** main chassis.

Technical Chars

- 1x RF coaxial input (F Female)
- Tuning of up to 4x **DVB-C (Annex A/C) multiplexes**
- 2x **PCMCIA Common Interface** slots
- **"Hot-swappable"** module
- **WEB interface based headend:** the module is managed through a friendly user HTML web interface to set every single parameter

GX-4C2CI-BP-00		
Code		287644
Bandwidth	MHz	6/7/8
Inputs		
Input no.		1 (4 Channels)
Front-end		
Input no.		4
Input band	MHz	47-862
Input level	dBuV	40-80
Demodulators		DVB-C: 16QAM/32QAM/64QAM/128QAM/256QAM
Modulazione di uscita		
Symbol rate	Mbit/s	3.6 ~ 6.952
Bandwidth	MHz	6/7/8
General features		
Connectors		1x F-female (RF)
Power Consumption	W	9.5
Common interface		2 x PCMCIA (Standard EN50221, TS10169) C.I.
Dimensions	mm	270x115x20
Working temperature	°C	-5 ÷ 50