

Remotelink Powered Amplifiers • 2, 4 & 6 Outputs

SPECIFICATION

Product Range:	A120D*	A240D*	A260D*
No. of Inputs / Outputs	1 / 2	2 / 4	2 / 6
Frequency Range	470-782MHz	45-230/470-782MHz	
Gain	8dB		
Noise Max	<4dB		
Max. Output*	78dBμV		
Isolation Between Outputs	>20dB		
Return Path Frequency	5-30MHz		
Impedance	75Ω		
Mains Power (Red LED)	230V AC ± 10% 50Hz		
Fitted Mains Plug	BS1363 3A rating		
* DIN 45004B 3 carriers, IMD3 - 60dB			

Product Range:	A120D/48**	A240D/48**	A260D/48**
No. of Inputs / Outputs	1 / 2	2 / 4	2 / 6
Frequency Range	470-694MHz	45-230/470-694MHz	
Gain	8dB		
Noise Max	<4dB		
Max. Output*	78dBμV		
Isolation Between Outputs	>20dB		
Return Path Frequency	5-30MHz		
Impedance	75Ω		
Mains Power (Red LED)	230V AC ± 10% 50Hz		
Fitted Mains Plug	BS1363 3A rating		



Remotelink amplifiers are suitable for UHF, VHF or SKY (RF2) distribution with a DC pass for control of source devices eg: SKY HD or SKY Q (with Conexer DMHD01E) and are compatible with ME200 magic eyes.



*RED: Radio Equipment Directive 2014/53/EU

Remotelink Powered Amplifiers • 8, 12 & 16 Outputs

SPECIFICATION

Product Range:	A280D*	A2120D*	A2160D*
No. of Inputs & Outputs	2 / 8	2 / 12	2 / 16
Frequency Range	45-230/470-782MHz		
Gain	8dB±2		
Noise Max	<4dB		
Max. Output*	78dBμV		
Isolation Between Outputs	>20dB		
Return Path Frequency	5-30MHz		
Impedance	75Ω		
Mains Power (Red LED)	230V AC ± 10% 50Hz		
Fitted Mains Plug	BS1363 3A rating		
* DIN 45004B 3 carriers, IMD3 - 60dB			

Product Range:	A280D/48**	A2120D/48**	A2160D/48**
No. of Inputs & Outputs	2 / 8	2 / 12	2 / 16
Frequency Range	45-230/470-694MHz		
Gain	8dB±2		
Noise Max	<4dB		
Max. Output*	78dBμV		
Isolation Between Outputs	>20dB		
Return Path Frequency	5-30MHz		
Impedance	75Ω		
Mains Power (Red LED)	230V AC ± 10% 50Hz		
Fitted Mains Plug	BS1363 3A rating		



Remotelink amplifiers are mains powered and offers full range from 2-16 output options to distribute small or large systems.



*RED: Radio Equipment Directive 2014/53/EU