

Remotelink[®] Infra Red (IR) Sensors • F-Type Connector



SPECIFICATION

Product:	ME200BKF
Female F connector	✓
Standard /Flat Screen TV	✓
LCD/Plasma Screen TV	✓
Black Colour	✓
Return Path Frequency	5-30MHz
Insertion Loss	<1dB
Control Commands	6MHz Carrier 38 KHz pulse
Power required	9V DC 15mA
Impedance	75Ω
Sensor Lead length	900mm
Connector Type	Male F Connectors
Trade Packed	✓

Extend the use of source devices in the home with the Remotelink Magic Eye IR Sensors. These allow the control of a source device such as a SKY HD box over a coax cable network. Compatible with Remotelink and 75 Series IR Pass amplifiers in trade or retail packs.



Remotelink[®] Infra Red (IR) Sensors • IEC Connector



SPECIFICATION

Product Range:	ME200BK	ME200BKF
IEC connector	✓	✓
Standard /Flat Screen TV	✓	✓
LCD/Plasma Screen TV	✓	✓
Black Colour	✓	✓
Return Path Frequency	5-30MHz	5-30MHz
Insertion Loss	<1dB	<1dB
Control Commands	6MHz Carrier 38 KHz pulse	
Power required	9V DC 15mA	
Impedance	75Ω	
Sensor Lead length	900mm	
Connector Type	IEC60169-2(m) male coax plug on 245mm fly lead	
Trade Packed	-	✓

The ME200 also available with coax connections ideal for use with the DMHD01E modulator to control SKYQ from up to 16 rooms when used with Remotelink amplifiers.

