

- 4 Years Warranty
- Compact size
- 16 x SAT inputs & 1 x TERR input
- 2 x 16 SAT + 2 TERR Outputs
- LTE Filter rejects 4G interference
- Green LED indicates DC power present
- Colour coded inputs & outputs
- 18V Auxiliary Input injects power to the HL & HH trunk lines
- Comes with 17 F-Type couplers for easy connection to Series 17 Multiswitches & Amplifiers



The Whyte Series 17 Splitter is a passive device designed to be used with the Whyte Series 17 IRS Multiswitch Range. The WS172-05 Splitter comes with 17 F-type Couplers for quick & easy insertion in to a cascade of Whyte Series 17 Multiswitches.

MODEL		WS172-05
Frequency	SAT	950-2150MHz
	TERR	87-790MHz
Inputs (F-Type Connector)		16 SAT + 1 TERR
Outputs (F-Type Connector)		2x 8 SAT + 2x TERR
DC Input (Injection of DC applied to)		SAT Trunk HL + HH
DC Pass Trunk to Tap	SAT	YES
	TERR	NO
DC Pass Trunk to Trunk	SAT	~
	TERR	~
Trunk Through Loss	SAT	~
	TERR	~
Tap Loss	SAT	4dB±1dB
	TERR	4dB±1dB
Fixed Slope Tap (SAT)		4dB
Isolation		>30db
Max Current Pass (Trunk/Trunk Trunk/Tap)		2A
Power Indication		LED
Dimensions W x L x H (mm)		278 x 278 x 43
Weight		1360g