



Superior product line

HomeSiren S Jeweller

Wireless siren with external LED connector.




- 2 GRADE EN 50131
- PD 6662 2017
- INCERT
- SSF
- NFA2P

What's new

Baseline HomeSiren Jeweller	Superior HomeSiren S Jeweller
SmartBracket mounting panel without holding screw	SmartBracket mounting panel with holding screw
Common battery	Enhanced battery
Available for all PROs	Available only for accredited partners

This is the device of the **Superior product line**. Superior products are advanced versions of Jeweller devices. This product line is developed for projects. Only accredited Ajax Systems partners can sell, install, and administer Superior products.



Informative alerts

The siren responds to tamper and security system alarms in less than a second. It is loud enough to scare away intruders and attract the attention of neighbours.

The siren LED notifies that the system is armed or disarmed, and a sound signal indicates delay when entering/leaving. These are helpful features for users who control the security system with a keypad or key fob.



Sabotage resistance

- Tamper alarm
- Device authentication to prevent spoofing
- Jamming detection
- Holding screw to secure the device on SmartBracket




Jeweller communication technology

- Up to 2,000 m of radio communication in an open space
- Data is encrypted throughout the transmission process
- Regular polling to display current device statuses




Event notifications

- Alarms of the system's devices
- Security status: armed/disarmed
- Door opening (Chime function)
- After-alarm indication



Flawless autonomy

- Up to 5 years of battery life
- Low battery notifications
- Panasonic pre-installed battery



Quick installation and setup

- Pairing with a hub via QR code
- Remote control and configuration in the app
- Effortless installation and replacement

<p>Compliance with standards</p> <p>EN 50131-4 (Grade 2) PD 6662:2017 INCERT SSF NFA2P</p> <p>Compatibility</p> <p>Hubs Hub Plus, Hub 2 (2G), Hub 2 (4G), Hub 2 Plus, Hub Hybrid (2G), Hub Hybrid (4G)</p> <p>Range extenders ReX, ReX 2</p>	<p>Communication with control panel</p> <p>Jeweller communication technology</p> <p>Frequency bands 868,0 – 868,6 MHz</p> <p>Communication range up to 2,000 m In an open space</p>	<p>Alerts</p> <p>Alarms Acoustic</p> <p>Delay When Entering/Leaving Acoustic</p> <p>Security mode change Acoustic, LED</p> <p>Security mode LED</p> <p>Door opening (Chime function) Acoustic</p> <p>After-alarm indication LED</p>	<p>Features</p> <p>Types of notifications Acoustic, LED</p> <p>Alarm volume from 81 to 105 dB at a distance of 1 m</p> <p>Alarm duration from 3 s to 3 min</p> <p>Piezoelectric buzzer frequency 3.5 ± 0.5 kHz</p> <p>Additional LED connection Available, 3 V$\overline{=}$</p>
<p>Power supply</p> <p>Battery 2 × CR123A</p> <p>Battery life up to 5 years</p>	<p>Installation</p> <p>Operating temperature range from -10°C to +40°C</p> <p>Operating humidity up to 75%</p> <p>Protection class IP50</p>	<p>Enclosure</p> <p>Colour white, black</p> <p>Dimensions 75 × 76 × 27 mm</p> <p>Weight 93 g</p>	<p>Complete set</p> <p>HomeSiren S Jeweller SmartBracket panel with holding screw 2 × CR123A batteries (pre-installed) Connector for third-party LED Installation kit Quick start guide</p>



For detailed information, scan the QR code or follow the link:

ajax.systems/support/devices/homesiren-s/

- ✉ support@ajax.systems
- 📍 @AjaxSystemsSupport_Bot
- 🌐 ajax.systems