

J31B



1-input (III+DAB+UHF) broadband TV indoor amplifier with 31dB gain and up to **124dB μ V output level**, gain adjustment (0-20dB) and low noise figure.

- **Push-pull configuration** with direct connection to mains.
- **Slope adjustment** (0-20dB) for cable losses.
- Metal die-cast shielded housing with F connectors and a plastic cover.
- **Excellent flatness.**
- It can be used as line amplifier in large distribution networks.
- 117dB μ V output level for analog signals.

ITEM	J31B
Code	223024
Input no.	1
Band	III+DAB + UHF
Gain (dB)	31
Gain adjustment (dB)	20 gain, 20 tilt
Noise figure (dB)	10
Output level (dB μ V)	124